

SIMPLE. DURABLE. INNOVATIVE.

CAST Impressionist LED Wall Wash (CIWL6) Product Information

Old world craftsmanship. . . tomorrow's technology™



Your Expression is our Passion!® The Impressionist Series® LED Wall Wash Light



Construction:

Solid bronze body, copper bracket; frosted lens; stainless steel set screws; 5' tin-coated #18-4 No-Ox® marine-grade power wire; control wire with capped connector.

Dimensions:

Body and bracket: 6" long x 3" x 4" tall wide.

Orientation:

Can be mounted in any orientation.

Specifications:

LED Light Source: (2) Cree LED's, Est. Life (L70) 51,400 hrs., 2,710° K, 82 CRI

Input Voltage: 10 to 24 V, AC or DC

Power: Amps: .73, Watts: 7.63, Power Factor: .88, VA 8.67

Lumen Output: 292 lm (from luminaire)

Center Beam Candela: 184

Listing:

cUL 1838 and 8750 Listed Low Voltage LED Luminaire for wet locations. FCC compliant. RoHs.

Description:

20 light levels means 20 combinations in 1 fixture! One Impressionist wall wash light replaces many retrofit lamps or integrated fixtures from other manufacturers. Less time planning, purchasing, and making adjustments in the field - all significant savings in time and labor.

This durable and advanced CAST LED Wall Wash Light (CIWL6) is a compact powerhouse that delivers illumination of exceptional quality. Designed for the landscape lighting professional, options include: light level control at the fixture and quick-change optics.

This fully sealed light can be used in any orientation (upward or downward facing). Multiple mounting kits enable the designer to use this light for down-washing or up-washing a wall, Elevating about bushes for a garden wash, or to wash retaining walls - a great fixture to provide a soft low-level wash on low-lying plant material - no hot spot!

Features:

Light Level Control

Light level is controlled by a dimming circuit built into the fixture. The circuit is accessed through a plug at the base of the light. By using the Dimming Control Module (CDIMMER) or the Manual Dimming Control Jumper Cable (CIJ - provided with fixture), you can change light level up or down in 5% increments. The light level that was set will remain after the controller is unplugged.

Uses:

Suitable for either up or down-lighting to provide a wide, bright, and diffuse illumination. Ideal for signs, walls, or plant material.